



- Battery charger and starter for 12/24V WET batteries and rapid cranking of all types of cars, vans, light goods vehicles, excavators, tractors and lorries.
- Fast (BOOST) charge and rapid cranking.
- Remote control. Timer to program timed BOOST charge and avoid overloading the battery.
- Display of charging and cranking current.
- Protection against overcharging and pole inversion.

## TECHNICAL DATA

CODE	<b>829008</b>	CHARGE AND STARTING VOLTAG.	<b>12 / 24 V</b>	MIN.RATED REFERENCE CAPAC.	<b>20 Ah</b>
THREEPHASE MAINS VOLTAGE	<b>230 / 400 V</b>	EFFECTIVE CHARGING CURRENT	<b>100 A</b>	MAX.RATED REFERENCE CAPAC.	<b>1600/ 800 Ah</b>
MAINS FREQUENCY	<b>50 / 60 Hz</b>	RATED CHAR.CUR.EN60335-2-29	<b>80 A</b>	ADJUSTMENT POSITIONS	<b>5</b>
CHARGING ABSORBED POWER	<b>2,5 kW</b>	START CUR.1V/C EN60335-2-29	<b>640 A</b>	DIMENSIONS (LxWxH)	<b>38 x 56 x 88,5 cm</b>
STARTING ABSORBED POWER	<b>20 kW</b>	MAX STARTING CURRENT	<b>1000 A</b>	WEIGHT	<b>45 kg</b>

## SUPPLIED ACCESSORIES

123467	CABLE 25 MMQ 3 M
123993	REMOTE CONTROL 6 M
123456	CABLE 25 MMQ 2,5 M
712025	POSITIVE CLAMP (+)
712026	WORK CLAMP

## ON REQUEST ACCESSORIES

BATTERY CHARGERS FUSES	
802129	FUSES 300A 10 PCS

## DESCRIPTION

Battery charger and starter for charging free electrolyte batteries (WET) with 12V/24V voltage and starting all kinds of cars, vans, light trucks, earth moving equipment, tractors and trucks.

Features:

- choice of normal charge, quick charge (BOOST), quick start;
- timer for quick charge;
- remote control;
- display of charging and starting current;
- protection against overloads and polarity reversal.

## DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST