



- Battery charger for 12/24V WET batteries. With ammeter. 110W.
- Protection against overcharging and pole inversion.

## TECHNICAL DATA

CODE	<b>807544</b>	CHARGING VOLTAGE	<b>12 / 24 V</b>	MAX.RATED REFERENCE CAPAC.	<b>115 / 40 Ah</b>
SINGLEPHASE MAINS VOLTAGE	<b>230 V</b>	EFFECTIVE CHARGING CURRENT	<b>9 / 4,5 A</b>	DIMENSIONS (LxWxH)	<b>17 x 25 x 16,5 cm</b>
MAINS FREQUENCY	<b>50 / 60 Hz</b>	RATED CHAR.CUR.EN60335-2-29	<b>6 / 3 A</b>	WEIGHT	<b>3,4 kg</b>
CHARGING ABSORBED POWER	<b>110 W</b>	MIN.RATED REFERENCE CAPAC.	<b>60 / 30 Ah</b>		

## SUPPLIED ACCESSORIES

123555	POSITIVE CABLE 1,5 MMQ 1 M
123556	WORK CABLE 1,5 MMQ 1 M
712623	COLORADO 40R POSITIVE CLAMP 40A
712624	COLORADO 40B WORK CLAMP 40A

## ON REQUEST ACCESSORIES

<b>BATTERY CHARGERS FUSES</b>	
802255	FUSES 10A 10 PCS

## DESCRIPTION

Battery charger for charging free electrolyte batteries (WET) with 12/24V voltage.  
Protected against overloads and polarity reversal.  
Equipped with ammeter.

## DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST