



- Battery charger for WET 12/24V batteries. With ammeter and normal or fast (BOOST) charge selector. 800W.
- Protection against overcharging and pole inversion.

TECHNICAL DATA

CODE	807547	CHARGING VOLTAGE	12 / 24 V	MAX.RATED REFERENCE CAPAC.	400 Ah
SINGLEPHASE MAINS VOLTAGE	230 V	EFFECTIVE CHARGING CURRENT	30 A	ADJUSTMENT POSITIONS	3
MAINS FREQUENCY	50 / 60 Hz	RATED CHAR.CUR.EN60335-2-29	20 A	DIMENSIONS (LxWxH)	22,5 x 29 x 20,5 cm
CHARGING ABSORBED POWER	800 W	MIN.RATED REFERENCE CAPAC.	15 Ah	WEIGHT	8,6 kg

SUPPLIED ACCESSORIES

123987	CABLE 4 MMQ 1,5 M AND WORK CLAMP
123988	CABLE 4MMQ 1,5M + POSITIVE CLAMP

ON REQUEST ACCESSORIES

BATTERY CHARGERS FUSES	
802256	FUSES 15A 10 PCS

DESCRIPTION

Battery charger for charging free electrolyte batteries (WET) with 12V/24V voltage. Protected against overloads and polarity reversal. Equipped with selector for normal or quick (BOOST) charge. Equipped with ammeter.

DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST