



**NEW**

**ELEMENTS**

12V

24V

Wet

EFB



- Battery charger and starter: WET/EFB 12/24V battery charger and rapid ignition of all types of vehicles, vans, etc. (300A max).
- Normal charge, boost, rapid ignition selection.
- Display of charging and ignition current.
- Protection against overcharging and pole inversion.

## TECHNICAL DATA

CODE	<b>829490</b>	CHARGE AND STARTING VOLTAG.	<b>12 / 24 V</b>	MIN.RATED REFERENCE CAPAC.	<b>20 Ah</b>
SINGLEPHASE MAINS VOLTAGE	<b>230 V</b>	EFFECTIVE CHARGING CURRENT	<b>45 A</b>	MAX.RATED REFERENCE CAPAC.	<b>700 Ah</b>
MAINS FREQUENCY	<b>50 / 60 Hz</b>	RATED CHAR.CUR.EN60335-2-29	<b>31 A</b>	ADJUSTMENT POSITIONS	<b>3</b>
CHARGING ABSORBED POWER	<b>1 kW</b>	START CUR.1V/C EN60335-2-29	<b>180 A</b>	DIMENSIONS (LxWxH)	<b>26,1x39,5x80,8cm</b>
STARTING ABSORBED POWER	<b>6,4 kW</b>	MAX STARTING CURRENT	<b>300 A</b>	WEIGHT	<b>15 kg</b>

## ON REQUEST ACCESSORIES

BATTERY CHARGERS FUSES	
802259	FUSES 50A 20 PCS

## DESCRIPTION

Battery charger and starter for charging WET/EFB batteries with 12V/24V voltage and starting all kinds of cars, vans and light trucks.

Features:

- Choice of normal charge, quick charge (BOOST), quick start;
- Display of charging and starting current;
- Protection against overloads and polarity reversal.

Equipped with cables with clamps.

## DOWNLOAD



CATALOG IMAGE



INSTRUCTION MANUAL



SPARE PARTS LIST